


1. Unzip the file to a folder you like and browser to that folder. You should see files as below.

Name	Date modified	Type	Size
amd64	19/11/2014 11:05 ...	File folder	
i386	19/11/2014 11:05 ...	File folder	
Static	19/11/2014 11:05 ...	File folder	
CDMUninstaller.exe	27/07/2010 8:12 AM	Application	563 KB
CDMuninstallerGUI.exe	26/07/2010 3:03 PM	Application	644 KB
cleandr.cmd	26/11/2014 11:22 ...	Windows Comma...	1 KB
dp-chooser.exe	22/10/2014 11:01 ...	Application	82 KB
dpinst.xml	22/10/2014 11:01 ...	XML File	20 KB
dpinst-amd64.exe	23/10/2014 1:16 AM	Application	1,023 KB
dpinst-x86.exe	23/10/2014 1:16 AM	Application	900 KB
ftd2xx.h	9/09/2014 8:42 PM	H File	40 KB
ftdibus.cat	10/09/2014 11:22 ...	Security Catalogue	14 KB
ftdibus.inf	26/11/2014 10:58 ...	Setup Information	13 KB
ftdiport.cat	10/09/2014 11:22 ...	Security Catalogue	13 KB
ftdiport.inf	26/11/2014 10:58 ...	Setup Information	14 KB
licence.txt	22/10/2014 11:01 ...	Text Document	9 KB
log_26-11-2014.txt	26/11/2014 11:03 ...	Text Document	0 KB
ReAssignCOMPortNumb.exe	23/11/2010 4:08 PM	Application	433 KB

2. Change a properties setting for dp-chooser.exe by right click on the file, select properties -> compatibility and tick  Run this program as an administrator  
If you don't do it, you may have issue as shown below.



3. Once finish, please unplug and plug back the USB cable of your cutter and wait for the driver to finish installing.
4. Run this program to set the cutter's Port and you need to remember it for the cutting program setup as shown below. The top USB Serial Port(COM#) is current port and the bottom port is the new port. The Port COM number need to be 1-4 for Artcut 2009 & Sign Blazer software. For Flexi-Starter 10, it can be any numbers.

